

# Digital Multimeter

## DM-97



### Features :

- 3¾ Digital Multimeter
- 4000 Counts Large LCD Display with Auto/Manual Range
- No Power-OFF under natural operation
- Data Hold, Max. / Min. Value Hold
- Capacitance, Frequency / Duty Cycle, Temperature and Transistor Test



### Technical Data :

Basic Functions	Range	Basic Accuracy
DC Voltage	0.1mV ~ 1000V	±(0.5% + 4digit)
AC Voltage	0.1mV ~ 750V	±(0.8%+ 6digit)
DC Current	0.1uA ~ 20A	±(1.0% + 5digit)
AC Current	0.1uA ~ 20A	±(1.5% + 5digit)
Resistance	0.1Ω ~ 40MΩ	±(0.8% + 2digit)
Capacitance	10pF ~ 200uF	±(3.5% + 8digit)
Frequency	0.1Hz ~ 30MHz	±(0.5% + 4digit)
Celsius	-40°C ~ 1000°C	±(0.8% + 4digit)
hhFE (NPN or PNP)	0 ~ 1000	

### Special Function :

Diode test	✓	Function Protection	✓
Transistor testing	✓	Input impedance	10MΩ
Continuity Buzzer	Lower 30Ω ±10Ω	Sampling Rate	3 times per second
Low Battery Display	Lower 2.4V	AC Frequency Response	40-400Hz
Auto Power OFF	Approx. 30 min.	Power	F3V AAA

- **Standard Accessories** : Test Leads, Holster, Manual, TP 01 Temperature Probe Bead type
- **Dimension** : 185(H) x 93(W) x 35(D)mm